#### Část 2 - 2D kamera pro orientaci robotického ramene

- Kamera Cognex IS2001M-230-S-LAB
- Rozlišení kamery 1.2Mpx
- Minimální zorné pole 10x7,5 mm
- Detekovatelné objekty cca 1-5% oproti požadovaným 10%
- Interní osvětlení: ano, LED červené
- Objektiv: 6,2mm vyměnitelný
- Autofocus žádná mechanika princip tekuté čočky
- Protokoly: přímá komunikace s UR robotem, další komunikační protokoly Profinet, ethernet IP, Modbus TCP,
- Video: <a href="https://www.youtube.com/watch?v=5QAgSxFvYJ0">https://www.youtube.com/watch?v=5QAgSxFvYJ0</a>

# COGNEX


field-changeable lighting and optics.

In-Sight® 2000 series vision sensors combine the power of an In-Sight vision system with the simplicity and affordability of a vision sensor. Ideal for solving error-proofing applications, these vision sensors set new standards for value, ease of use, and flexibility thanks to a powerful combination of proven In-Sight vision tools, simple setup, and a modular design featuring

**IN-SIGHT 2000 SERIES VISION SENSORS** 

The In-Sight Explorer™ EasyBuilder® interface, which provides fast, step-by-step application setup, allows even novice users to achieve extremely reliable inspection performance in nearly any production environment.


In-Sight 2000 series vision sensors are available in two form factors. This modular body design provides maximum flexibility to mount in tight spaces, allows for customized wiring and optical paths, and minimizes the need to design new mechanical fixtures.






















- Affordable vision sensor powered by In-Sight Explorer software and EasyBuilder—the same interface used for all In-Sight vision systems
- Simple for both new and existing users to meet their automated inspection challenges
- Monochrome and color sensor models solve presence/absence applications, including color verification
- Proven, reliable Cognex In-Sight vision tools
- Compact, modular design with field-changeable, integrated optics and lighting
- Autofocus lens eliminates the need to manually refocus or adjust the mounting height of the sensor during line changeovers
- Fully compatible with Cognex VisionView® PC software and VisionView 900 HMI touchscreen panel
- Single-cable Power over Ethernet (PoE) models simplify installation

### Fast, intuitive setup with EasyBuilder


With its intuitive, point-and-click presence/absence tools, the EasyBuilder interface is ideal for setting up simple pass/fail inspections. When more complex inspections are required, users can build on their experience to create vision applications using more advanced In-Sight vision systems in the same In-Sight Explorer interface.




### A solution for any industry

In-Sight 2000 series vision sensors deliver simple pass/fail results across a wide range of applications in multiple industries. Powerful vision tools deliver robust inspection results for parts in all shapes and sizes. Below, a contrast tool is used to detect the presence of a gasket in an electronics sub-assembly, a pixel count tool is used to identify QA marks on an automotive part, and a color pixel count tool is used to inspect the proper packaging for a fruit snack.

#### **Electronics**



#### **Automotive**



#### Food and Beverage



# Choice of lighting and optics for different application requirements

In-Sight 2000 series models include an integrated lens and LED illumination that eliminate the need for costly external lighting. Lenses and lighting are field-interchangeable to adjust to different application requirements. The In-Sight 2000 Mini has a smaller form factor making it ideal for mounting in tight spaces.




# A model for any application

Available in both monochrome and color image models, and with different combinations of vision tools, the In-Sight 2000 series lets you choose the level of capability you need. Whatever your inspection application, there's an In-Sight 2000 vision sensor model that's right for the job.

| IN-SIGHT 2000                          |                              | 2000-110   | 2000-120                        | 2000-130 | 2000-230 | 2001-230                        |  |  |
|--|------------------------------|--|---------------------------------|----------|----------|---------------------------------|--|--|
|  |                              | 2000-110   |                                 |          |          |                                 |  |  |
| User Interface                         |                              | In-Sight Explorer EasyBuilder, Cognex VisionView PC Software,<br>and VisionView 900 HMI touchscreen panel  |                                 |          |          |                                 |  |  |
| 1/3" CMOS Imager, Global Shutter       |                              | Monochrome and Color   |                                 |          |          |                                 |  |  |
| •                                      |                              | Standard: Autofocus (liquid lens) 6.2 mm or manual focus 8 mm  |                                 |          |          |                                 |  |  |
| S-Mount/M12 Lenses                     |                              | Optional: Manual focus 3.6 mm, 6 mm, 12 mm, 16 mm, 25 mm   |                                 |          |          |                                 |  |  |
| Image Modes                            | 640 x 480 (standard)         | ✓  | ✓                               | ✓        | ✓        | ✓                               |  |  |
|  | 640 x 480 (2x magnification) | ×  | ✓                               | ✓        | ✓        | ✓                               |  |  |
|  | 800 x 600 (2x magnification) | ×  | ×                               | ✓        | ✓        | ✓                               |  |  |
|  | 1280 x 960 <sup>1</sup>      | ×  | ×                               | ×        | ×        | ✓                               |  |  |
| Lighting                               | Standard                     | Diffuse white LED ring light   |                                 |          |          |                                 |  |  |
|  | Options                      | Red, blue and IR LED ring lights and lens filters, and polarized light cover   |                                 |          |          |                                 |  |  |
| Maximum Acquisition Speed <sup>2</sup> |                              | 40 fps   | 75 fps (mono)<br>55 fps (color) |          |          | 40 fps (mono)<br>24 fps (color) |  |  |
| Relative Processing Speed              |                              | 1x   | 1x 2x                           |          |          |                                 |  |  |
| Location Tools                         | Pattern                      | ✓  | ✓                               | ✓        | ✓        | ✓                               |  |  |
|  | Edge, Circle                 | ×  | ×                               | ✓        | ✓        | ✓                               |  |  |
|  | Pattern                      | ✓  | ✓                               | ✓        | ✓        | ✓                               |  |  |
| Inspection Tools                       | Pixel Count                  | x Grayscale and color  |                                 |          |          |                                 |  |  |
|  | Brightness & Contrast        | ×  | ✓                               | ✓        | ✓        | ✓                               |  |  |
|  | Edges                        | ×  | ×                               | ✓        | ✓        | ✓                               |  |  |
| Measurement &                          | Distance, Angle & Diameter   | ×  | ×                               | ✓        | ✓        | ✓                               |  |  |
| Counting Tools                         | Patterns & Edges             | ×  | ×                               | ✓        | ✓        | ✓                               |  |  |
| Advanced<br>Features                   | OCR                          | ×  | ×                               | ×        | ✓        | ✓                               |  |  |
|  | Blob Detection               | ×  | ×                               | ×        | ✓        | ✓                               |  |  |
|  | Image Filters                | ×  | ×                               | ×        | ✓        | ✓                               |  |  |
| Data Output                            |                              | Pass/Fail Pass/Fail, Numeric <sup>3</sup>  |                                 |          |          |                                 |  |  |
|  | General Protocols            | TCP/IP, UDP, FTP, Telnet, RS-232C  |                                 |          |          |                                 |  |  |
| Communications & I/O                   | Industrial Protocols         | OPC UA, EtherNet/IP with AOP, PROFINET Class B, iQSS, SLMP, SLMP Scanner, CC-Link IE Field Basic, Modbus TCP   |                                 |          |          |                                 |  |  |
|  | Connectors                   | (1) Industrial M12 Ethernet, (1) M12 Power & I/O   |                                 |          |          |                                 |  |  |
|  | Inputs & Outputs             | (1) Acquisition trigger, (1) General purpose input <sup>4</sup> , (4) General purpose outputs <sup>4</sup>   |                                 |          |          |                                 |  |  |
| Mechanical                             | Dimensions                   | In-line configuration: 92 mm (3.61 in) x 60 mm (2.38 in) x 52 mm (2.05 in)<br>Right-angle configuration: 61 mm (2.42 in) x 60 mm (2.38 in) x 52 mm (2.05 in) |                                 |          |          |                                 |  |  |
|  | Weight                       | 200 g (7.05 oz)  |                                 |          |          |                                 |  |  |
|  | Material and Protection      | Painted aluminum, IP65-rated housing   |                                 |          |          |                                 |  |  |
| Operating                              | Power                        | 24 VDC ±10%, 48 W (2.0 A) maximum when the illumination is on  |                                 |          |          |                                 |  |  |
|  | PoE Configuration Available  | No   |                                 |          |          |                                 |  |  |
|  | Temperature                  | 0 °C to 40 °C (32 °F to 104 °F)  |                                 |          |          |                                 |  |  |

 $<sup>^{\</sup>mbox{\tiny 1}}$  Available in select regions. Ask your Cognex sales representative for more information.

<sup>&</sup>lt;sup>4</sup> (7) general purpose inputs and (8) general purpose outputs when using optional CIO-1400 I/O Expansion Module.




<sup>&</sup>lt;sup>2</sup> Maximum framerate with minimum exposure; no vision tools; and 640 x 480 image with 2x Image Magnification enabled (for 2000-120/130/230 models).


 $<sup>^{\</sup>scriptscriptstyle 3}$  Limited to Measurement & Counting Tools only.

|  |                              | 2000-110 Mini  | 2000-120 Mini  | 2000-130 Mini | 2000-230 Mini | 2001-230 Min                    |  |  |  |
|--|------------------------------|--|--|---------------|---------------|---------------------------------|--|--|--|
| User Interface                         |                              | In-Sight Explorer EasyBuilder, Cognex VisionView PC Software, and VisionView 900 HMI touchscreen panel   |  |               |               |                                 |  |  |  |
| 1/3" CMOS Imager, Global Shutter       |                              | Monochrome Monochrome and Color  |  |               |               |                                 |  |  |  |
| S-Mount/M12 Lenses                     |                              | Autofocus (liquid lens) 6.2 mm or 16 mm  |  |               |               |                                 |  |  |  |
| Image Modes                            | 640 x 480 (standard)         | ✓  | ✓  | ✓             | ✓             | ✓                               |  |  |  |
|  | 640 x 480 (2x magnification) | ×  | ✓  | ✓             | ✓             | ✓                               |  |  |  |
|  | 800 x 600 (2x magnification) | ×  | ×  | ✓             | ✓             | ✓                               |  |  |  |
|  | 1280 x 960 <sup>1</sup>      | ×  | ×  | ×             | ×             | ✓                               |  |  |  |
|  | Standard                     | Modular red LEDs Modular red (mono) and white (color) LEDs   |  |               |               |                                 |  |  |  |
| Lighting                               | Options                      | White, blue & IR LED lights, band-pass filters & polarizing filter   | White, blue & IR LED lights, band-pass filters, polarizing filter, and polarized light cover |               |               |                                 |  |  |  |
| Maximum Acquisition Speed <sup>2</sup> |                              | 40 fps   |  |               |               | 40 fps (mono)<br>24 fps (color) |  |  |  |
| Relative Processing Speed              |                              | 1x   | 2x   |               |               |                                 |  |  |  |
| Location Tools                         | Pattern                      | ✓  | ✓  | ✓             | ✓             | ✓                               |  |  |  |
|  | Edge, Circle                 | ×  | *  | ✓             | ✓             | ✓                               |  |  |  |
| Inspection Tools                       | Pattern                      | ✓  | ✓  | ✓             | ✓             | ✓                               |  |  |  |
|  | Pixel Count                  | ×  | Grayscale Grayscale and color  |               |               |                                 |  |  |  |
|  | Brightness & Contrast        | ×  | ✓  | ✓             | ✓             | ✓                               |  |  |  |
|  | Edges                        | ×  | ×  | ✓             | ✓             | ✓                               |  |  |  |
| Measurement & Counting Tools           | Distance, Angle & Diameter   | ×  | ×  | ✓             | ✓             | ✓                               |  |  |  |
|  | Patterns & Edges             | ×  | ×  | ✓             | ✓             | ✓                               |  |  |  |
| Advanced<br>Features                   | OCR                          | ×  | ×  | ×             | ✓             | ✓                               |  |  |  |
|  | Blob Detection               | ×  | ×  | ×             | ✓             | ✓                               |  |  |  |
|  | Image Filters                | ×  | ×  | ×             | ✓             | ✓                               |  |  |  |
| Data Output                            |                              | Pass/Fail Pass/Fail, Numeric <sup>3</sup>  |  |               |               |                                 |  |  |  |
| Communications & I/O                   | General Protocols            | TCP/IP, UDP, FTP, Telnet, RS-232C  |  |               |               |                                 |  |  |  |
|  | Industrial Protocols         | OPC UA, EtherNet/IP with AOP, PROFINET Class B, iQSS, SLMP, SLMP Scanner, CC-Link IE Field Basic, Modbus TCP   |  |               |               |                                 |  |  |  |
|  | Connectors                   | (1) Industrial M12 Ethernet, (1) M12 Power & I/O   |  |               |               |                                 |  |  |  |
|  | Inputs & Outputs             | (1) Acquisition trigger, (1) General purpose input <sup>4</sup> , (4) General purpose outputs <sup>4</sup>   |  |               |               |                                 |  |  |  |
| Mechanical                             | Dimensions                   | In-line configuration: 43.1 mm (1.69 in) x 22.4 mm (0.88 in) x 64 mm (2.51 in)  Right-angle configuration: 43.1 mm (1.69 in) x 35.8 mm (1.40 in) x 49.3 mm (1.94 in) |  |               |               |                                 |  |  |  |
|  | Weight                       | 142 g (5 oz)   |  |               |               |                                 |  |  |  |
|  | Material and Protection      | Painted aluminum, IP65-rated housing   |  |               |               |                                 |  |  |  |
| Operating                              | Power                        | 24 VDC ±10%, <3.0 W or Class 1 Power over Ethernet (PoE) <sup>5</sup>  |  |               |               |                                 |  |  |  |
|  | PoE Configuration Available  | ×  | ✓  | ✓             | ✓             | ✓                               |  |  |  |
|  | Temperature                  | 0 °C to 40 °C (32 °F to 104 °F)  |  |               |               |                                 |  |  |  |

<sup>&</sup>lt;sup>1</sup> Available in select regions. Ask your Cognex sales representative for more information.

<sup>&</sup>lt;sup>5</sup> PoE models cannot use a 24 VDC power supply and vice versa.






<sup>&</sup>lt;sup>2</sup> Maximum framerate with minimum exposure; no vision tools; and 640 x 480 image with 2x Image Magnification enabled (for 2000-120/130/230 models)

 $<sup>^{\</sup>scriptscriptstyle 3}$  Limited to Measurement & Counting Tools.


<sup>&</sup>lt;sup>4</sup> (7) general purpose inputs and (8) general purpose outputs when using optional CIO-1400 I/O Expansion Module.

# **Field of View Diagrams**

In-Sight 2000



In-Sight 2000 Mini



# COGNEX

Companies around the world rely on Cognex vision and barcode reading solutions to optimize quality, drive down costs and control traceability.

Corporate Headquarters One Vision Drive Natick, MA 01760 USA

#### Regional Sales Offices

#### **Americas**

North America +1 844-999-2469 Brazil +55 (11) 2626 7301 Mexico +01 800 733 4116

Europe

Austria +49 721 958 8052 Belgium +32 289 370 75 France +33 1 7654 9318 Germany +49 721 958 8052 Hungary +36 800 80291 +44 121 29 65 163 Ireland +39 02 3057 8196 Italy +31 207 941 398 Netherlands Poland +48 717 121 086 +34 93 299 28 14 Spain Sweden +46 21 14 55 88 +41 445 788 877 Switzerland +90 216 900 1696 United Kingdom +44 121 29 65 163

Asia China +86 21 6208 1133 +9120 4014 7840 India +81 3 5977 5400 Japan +82 2 539 9980 Korea +6019 916 5532 Malaysia Singapore +65 632 55 700 +886 3 578 0060 Taiwan Thailand +66 88 7978924 +84 2444 583358 Vietnam

© Copyright 2019, Cognex Corporation.
All information in this document is subject to change without notice. All Rights Reserved. Cognex, In-Sight, EasyBuilder and VisionView are reigstered trademarks of Cognex Corporation. In-Sight Explorer is a trademark of Cognex Corporation. All other trademarks are property of their respective owners. Lit. No. DSIS2000-10-2019

www.cognex.com